

Product information:

The TRM series are 70/100V line transformers that can be optionally implemented in the passive variants of the VEXO series. Installation is done by removing the backplate of the VEXO series (passive variants only) and replacing it with a 70/100V backplate on which the module is integrated. Like this, the high-performance loudspeaker can be implemented in 70/100V systems.



Voltage:

 70-100 Volt

Usage:



Indoor

System specifications:

Line Transformer Tappings	1	41.67 Ω - 100 V / Not used - 70 V / 120 W
	2	83.33 Ω - 100 V / 120 W - 70 V / 60 W
	3	166.67 Ω - 100 V / 60 W - 70 V / 30 W
Impedance		8 Ω (secondary)
		4 Ω (secondary)
Connection		External (to amplifier) - 8-pin terminal block
		Internal (to speaker) - 3-pin connector
Frequency	Response (\pm 3 dB)	50 Hz - 20 kHz

Product Features:

Construction		Aluminum backplate
		Copper toroidal transformer
Colours		Black (RAL9005)
Accessories	Included	M8 x 80 mm (mounting bolt)
		null
		null
		null
Compatible devices		null
		VEXO106
		VEXO108
		VEXO206
		VEXO208

Variants:

- TRM012/B - Black version