

Product information:

The TRM series are 70/100V line transformers that can be optionally implemented in the passive variants of the VEXO series. Installation is done by removing the backplate of the VEXO series (passive variants only) and replacing it with a 70/100V backplate on which the module is integrated. Like this the high-performance loudspeaker is able to be implemented in 70/100V systems.



Voltage:

⚡ 70-100 Volt

Usage:



Indoor

System specifications:

Line Transformer Tappings	1	20.83 Ω - 100 V / Not used - 70 V / 240 W
	2	41.67 Ω - 100 V / 240 W - 70 V / 120 W
	3	83.33 Ω - 100 V / 120 W - 70 V / 60 W
Impedance	8 Ω (Secondary)	
Connection	External (to amplifier) - 8-pin terminal block	
	Internal (to speaker) - 2-pin connector	
Frequency	Response (± 3 dB)	50 Hz - 20 kHz

Product Features:

Construction	Aluminium backplate	
	Copper toroidal transformer	
Colours	Black (RAL9005)	
	White (RAL9003)	
Compatible devices	VEXO112	
	VEXO115	
Accessories	Included	M8 x 80 mm (Mounting bolt)
		null

Variants:

- TRM224/B - Black version - VEXO112 & VEXO115 - 240W & 120W power taps
- TRM224/W - White version - VEXO112 & VEXO115 - 240W & 120W power taps